

Compact LED Emergency Light Fitting for Ex-Zones 2/22

Series nD8611/... LED



Application:

Hazardous locations of zones 2 (gas) and 22 (dust) for illumination of escape routes and for identification of escape routes.

Design:

Housing: Diecast aluminium, natural finish, gear set located inside the housing, wired ready for connection.

Cover: Polycarbonate opalescent white,

(W), foamed silicone gasket. (Pictograms – if required – to be ordered separately, see accessories).

Connection terminal: 3 or 4 poles, clamping range max. 2,5mm².

Cable entries: 1 cable gland M20 x 1,5 on the front side.

Mounting: 2 outer fixing points.

Technical Data:

LED: Highpower-LED, 6.500K, CRI > 70, L₇₀B₁₀ > 50.000h at max. ambient temperature

Versions with self-contained battery:

Built-in NiMH battery. A constant trickle charge to the battery ensures readiness of operation at all times.

Automatic monitoring the emergency light fitting acc. to EN 62034. Indication of the test results by 2-colour LED on the light fitting.




Electronic deep discharge protection acc. to EN 61347-2-7

Recharging time: 24 h, acc. to EN 60598-2-22

Modes of operation: Maintained or stand-by operation

Options:

- cable looping on one side
- ECG for safety extra-low voltage (24VDC)
- for different ambient temperatures



SCHUCH Quality - your advantage:


- safety in case of an emergency, instant light with maximum light output also at low temperatures
- stable luminous flux in emergency operation independent from the ambient temperatures
- outstanding visibility of the indication sign due to a superb and even illumination of the pictogram
- reduced battery capacity
- robust fitting for rough environment
- perfect by strained field conditions
- homogeneous illumination by using frosted diffusers, comfortable perception of light
- fast mounting through external mounting grounding clips

Article no.	Type	Power consumption [W] *	Luminous flux [lm] *	Luminous flux [lm] * (emergency)	Luminous efficacy [lm/W]	1h operation time	3h operation time	Energy efficiency class	Weight [kg] (without packing material)

nD8611/201/. W



emergency light fitting with built-in battery



Ignition protection: nR

Explosion protection:

II 3 G Ex nR IIC T4 Gc Gc (Zone 2)

II 3 D Ex tc IIIC T80°C Dc (Zone 22)

Rated voltage: 220-240V AC, 50/60Hz

Ambient temperature:

-5°C bis +30°C (maintained operation)

-0°C bis +40°C (standby operation)

86111 0002	nD8611/201/1W	5	100	100	20	•		A++	1,0
86111 0003	nD8611/201/3W	5	100	100	20		•	A++	1,2

* see notes

Notes:



Properties, limitations and details for controlling LED-light fittings: See „Technical Supplement“.

All technical data is relevant at the time of print.

Actual technical data can be found in the internet under www.schuch.de.

Article no.	Type	Power consumption [W] *	Luminous flux [lm] *	Luminous flux [lm] * (emergency)	Luminous efficacy [lm/W]	1h operation time	3h operation time	Energy efficiency class	Weight [kg] (without packing material)
-------------	------	-------------------------	----------------------	-------------------------------------	--------------------------	-------------------	-------------------	-------------------------	---

nD8611/201 W



Ignition protection: nR

Rated voltage: 220-240V AC, 50/60Hz

Explosion protection:

Ambient temperature:

II 3 G Ex nR IIC T4 Gc Gc (Zone 2)

-20°C up to +40°C

II 3 D Ex tc IIIC T80°C Dc (Zone 22)

(further versions upon request).

86110 0001	nD8611/201W	4	100	25			A++	0,8
------------	-------------	---	-----	----	--	--	-----	-----

for connection to central power supply unit

86111 0301	nD8611/201W ZB	4	100	25			A++	0,8
------------	----------------	---	-----	----	--	--	-----	-----

* see notes

Explosion protected
Light Fittings



Type nD8611/... with pictogram 220/110/35

Self-adhesive pictogram



220/110/33 .../34 .../35

For marking escape routes acc.to DIN EN ISO 7010 and ASR A1.3.

Viewing = 22m.

Accessories / Spare Parts

Article no.	Type	
Spare cover		
36004 9002	3611/02	PC, white opalescent
Self adhesive legends for series 3611 and 8611		
12112 0101	220/110/33	Emergency exit to the left
12112 0102	220/110/34	Emergency exit to the right
12112 0103	220/110/35	Emergency exit below
Cable entries		
90120 9008	2531 G	Ex-plastic cable gland M20 x 1,5 with nut
90121 9005	2532 G	Ex-plastic cable gland M20 x 1,5 with plug and with nut
Spare-batteries		
90222 9026	Akku 8620	Spare-battery 1h
90222 9027	Akku 8621	Spare-battery 3h